

MPI 4

MAXIMUM PERFORMANCE INDICATOR / FM MULTIPATH TUNING INDICATOR

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Calibrated reticle screen. POWER LED column in 10dB steps from 0.1W to 1000W. PREAMP LED indicator. SWEEP. HORIZONTAL. VERTICAL. INTENSITY. POWER LEVEL. GAIN with on/OFF switch. ⚡ Pushbutton switches: SWEEP FREQUENCY: 20-200, 200-2K, 2K-20K. MODE SELECTOR: L, (DUAL TRACE), R, LEVEL, STEREO, MULTIPATH. INPUT AUDIO jack. PANLOC buttons.



BACK PANEL: Power cord. FUSE. Unswitched AC outlet. POWER AMP: Push terminals for: LEFT and RIGHT speaker inputs. SPEAKER IMPEDANCE switch: 4 Ω, 8 Ω or 16 Ω. PREAMP: LEFT AUDIO INPUT, LEFT AUDIO OUTPUT, RIGHT AUDIO INPUT, RIGHT AUDIO OUTPUT. TUNER: SIGNAL STRENGTH (TP 1), DEVIATION (TP 2). Panloc mounting.



TOP PANEL: LEVEL MODE: NORMAL, PEAK, RESET. RETICLE ILLUMINATION: OFF or ON. LOW PASS FILTER: OUT or IN. FOCUS. SWEEP: TRIGGER SOURCE: LEFT, RIGHT, LINE, TRACE SEPARATION: MIN to MAX, SWEEP EXPANSION: 0.25 to 5. TUNER: MULTIPATH POLARITY + or -, SIGNAL STRENGTH, DEVIATION. AUDIO TRIM: LEFT and RIGHT.

MPI 4

MAXIMUM PERFORMANCE INDICATOR / FM MULTIPATH TUNING INDICATOR

McIntosh

The Compendium

SPECIFICATIONS: Multipath mode: sensitivity 100mV/cm, response dc to 50kHz (-3dB), input impedance 250k, signal strength polarity positive or negative. Stereo mode: sensitivity (vertical and horizontal) 1.75mV rms/cm (5mV p-p/cm), response 5Hz to 50kHz (-3dB), input impedance 250k. Power level mode: sensitivity 0.1 to 1000 average watts for full scale indication (+3dB) in 9 calibrated steps, response 5Hz to 100kHz (-3dB). Input impedance 75k, sensitivity 0.1 to 1000 average watts for full scale indication (+3dB) in 9 calibrated steps, response 5Hz to 100kHz (-3dB). Input impedance 75k, calibration for 4, 8 and 16 ohm loads. Preamp mode: sensitivity 15mV rms for +3dB indication, response 5Hz to 50k, input impedance 250k. Sweep mode: display modes: left, right or dual trace, sensitivity 1.6mV rms/cm (4.5mV p-p/cm), response 5Hz to 50kHz (-3dB), input impedance 250k, sweep frequency 20-20kHz in 3 decade ranges, sweep expansion 0.25X to 5X, sweep triggers only when signal present, selectable trigger channel in dual trace mode. Level mode times: Normal:250usec rise and 500ms decay, peak: 500usec rise and 25sec decay, reset: 250usec rise and 100 sec decay. Low pass filter: 16kHz LF filter for stereo and sweep modes, 19kHz and 38kHz rejected by 30dB. CRT 3" round tube calibrated 5X6 cm. Reticule lights: multipath = blue, stereo = red, level = amber, sweep = green.



MPI 4 - Sold from July 1973 - May 1977. S/N: AF1001~AF2793 (1,792 units)

Size: 5-7/16"H, 16"W and 13"D. Weight 21 lb. **\$599.00**