

MR 7082

AM - FM STEREO TUNER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. Indicators for: FM, AM, SEARCH, MONO, MONOPLUS, STEREO. Digital frequency readout. FM MPX light. TUNING lights: ▶, • (lock) and ◀. LED indicators for SIGNAL strength. ⚡ Push Buttons: FM, AM, SEARCH, MANUAL, POWER, MONO, MONOPLUS, STEREO. Preset stations with indicator lights: 1, 2, 3 and 4, SCAN ▲. Preset stations with indicator lights: 5, 6, 7, SCAN ▼, ENTER. Tuning control with manual tuning indicator light. PANLOC buttons.



EARLY



LATE

BACK PANEL: Power cord. 75 Ω FM ANTENNA coax input. Push terminals for GND and external AM ANTENNA. 15 pin REMOTE CONTROL receptacle. Left & Right fixed AUDIO OUTPUT. (late units had FIXED and VARIABLE outputs and an OUTPUT LEVEL adjustment). Panloc mounting.

FM SECTION: Sensitivity 13dB μ V or 1.22 μ V across 75 ohms. Stereo 50dB quieting sensitivity 37dB μ V or 20 μ V across 75 ohms. Response 20-15kHz (+0 -1dB). Distortion 0.08% in stereo. Capture ratio 1.5dB. Image rejection 90dB. S/N 75dB stereo. Alternate channel selectivity 55dB. Spurious rejection 100dB. AM suppression 60dB.

AM SECTION: Sensitivity 35 μ V. Response 20-4.5kHz (+0 -6dB). Distortion 0.3%. Adjacent channel selectivity 40dB. S/N 65dB. Image rejection 60dB.

MR 7082

AM - FM STEREO TUNER

McIntosh
The Compendium



MR 7082 - Sold from May 1986 - 1990. S/N: EE1001~?????

Size 5-7/16"H, 16-1/8"W and 13"D behind panel. Weight 15 lb. **\$1,579.00**